

# OSD MX1260 12-Channel Bridgeable Amplifier

## Product Description

The most powerful and efficient multi-channel amp in its price range, the OSD-MX1260 is a 6-zone, 12-channel power amp for use in distributed audio applications and for main power in dedicated home theaters.

## Features

Rated at 40 Watts per channel RMS at 8 ohms, the MX1260 is a serious contender for complex audio systems and will distribute sound to 12 different locations without the risk of overload. Equipped with brains and brawn, the MX1260 includes 6 zones or 12 channels (speakers), so owning this amp is like having six 2-channel amps in one efficient location.

- Unique bus system distributes an audio signal from one source to multiple locations
- Individual output level controls for each channel
- Signal sensing, sensing on 5-24V trigger and three power-up options
- Brushed aluminum finish and OSD's signature "built-like-a-brick" construction
- 2-year warranty



## The Specs

- 40 Watts per channel RMS at 8 ohms
- 60 Watts per channel RMS at 4 ohms
- Bridged Power Output: 80 Watts per channel RMS at 8 ohms (8 ohm minimum)
- Input Sensitivity: 380 mV for full output with all level controls at max
- Input Impedance: 18K ohm
- Frequency Response: 5 Hz to 72 kHz
- Distortion: .09% THD 20 Hz-20 kHz @ 40W (8 ohm)
- Distortion (Bridged): .30% THD 20 Hz 20 kHz @ 80W (8 ohm)
- Channel Crosstalk: 80 dB
- Signal to Noise Ratio: 95 dB A-weighted
- Efficiency: 60%
- Multi-voltage 115VAC/230VAC
- Auto Turn-On Sensitivity: 18.84mV
- Dimensions: 16.7W x 4"H (include feet) x 14.25"D
- Net Weight: 34 lbs
- Rack Mountable



Find the MX1260 at Outdoor Speaker Depot,  
[www.outdoorspeakerdepot.com](http://www.outdoorspeakerdepot.com)  
or call 888 779-4968.