



XMP300BT Wireless Amplifier

XMP300BT amplifier makes a great choice for powering speakers in your home, studio or desktop sound system. This versatile amp's 24/192 USD Audio, BT Wireless and dual line-level inputs let you enjoy sound from one main music source plus an additional interrupting audio source, switching automatically between them.

The XMP300BT is designed for dedicated stereo & distributed audio applications. It offers many features including A & B speaker outputs. USB Type A 24/194 HD Audio, plus BT wireless as well as RCA Line In, and Interrupt Line In inputs. It can also be configured for Stereo or Bridged output, delivering up to 600 watts.

SPECIFICATIONS

- Class D Amplifier: Stereo Four Channel (2A, 2B)
- Wireless BT: V5.3
- Rated Output Power: 600W
- 8Ohm - 150W x 2 Channel RMS/Output 8Ohm
- 4Ohm - 300W x 2 Channel RMS/Output 4Ohm
- Bridged Mono 600W x 1 Channel RMS (A or B) @ 8Ohm
- Frequency Response: 20Hz - 20kHz
- Impedance: 8Ohm to 4Ohm Stable
- Signal to Noise Ratio: 90>dB 300W output into 4Ohm
- 20kHz Low-pass Filter
- Channel Separation: 50dB @ 1kHz referred to 150W Output into 8Ohm
- Input Sensitivity: 700mV Input Rated 150W Output into 8Ohm
- Sources/Inputs: Wireless BT / USB / Line In (Interrupt/ Main)
- Output: Signal (low) level/Speaker (High) Level Outputs
- THD: «1% @ output Rated power / « 0.07% @ output 1~240W
- Bass and Treble Controls: (+/-) 12dB @ 100Hz and 10kHz
- Other Back Panel Controls: Trigger Functions/Bridged Mono-Stereo
- Front Panel Controls: Speaker (A/B) / Balance / Volume
- AC Power: Multi-Voltage 100V-240V 50-60Hz / 250V
- Dimensions: 16.92" x 1.73" x 7.92"
- Weight: 8lbs
- 2 Year Warranty