



NERO STREAM XD2 Streaming Amp

A versatile integrated wireless amp/preamp that opens up a new world of high-fidelity sound featuring Wi-Fi streaming which connects to your home network allowing it to operate independently from your Smartphone. Instead the Wi-Fi connection is controlled by our free OSD Player app from Bluetooth-compatible devices such as smartphones and tablets. This compact, stand-alone amplifier uses Wi-Fi and an upgraded version of Bluetooth (APXT) to transmit sound but also includes wired inputs so you can stream through classic 2-channel stereo systems and your beloved tower speakers as well as devices such as Google Chromecast or Amazon Alexa.

SPECIFICATIONS

- Amplifier Type: Stereo
- Design Type: Class D
- DAC: Cirrus Logic CS8416 24 Bit/192kHz DAC
- Wi-Fi Frequency: 2.4 GHz
- Bluetooth Version: 4.2 w/ aptX™
- Max Peak Output Power: 400W
- 8 Ohm Rating (Watts): 60W Per Ch. continuous RMS
- 4 Ohm Rating (Watts): 120W Per Ch. continuous RMS
- Frequency response: 20Hz ~ 20KHz
- Sensitivity: Digital, 0db input; Analog, 0.6Vrms
- Impedance: 8-ohms to 4-ohm stable
- Signal to Noise Ratio >95dB A-weighted
- Sources/Inputs: Wi-Fi®, Bluetooth®, Optical, USB, RCA Stereo Line-In
- Outputs: Dedicated Subwoofer (low pass filter @500Hz, Mono/RCA 1/4" Headphone Jack (front panel)
- Front Panel Status LEDs
- Dual function volume and source selection knob
- Power: Selectable Multi-Voltage Switch (100/240V)
- Master On/Off (back panel)
- Includes WPS button to interface with router
- Dimensions: 9.5 x 8.5 x 2.5" inch
- Weight: 6.8 lbs